



Quick Look

Number of Ethernet WAN port	0 / 1 (FE) ^[1]	[1] WAN port(s) can be configured as LAN port(s) via the Web Admin.
Number of Ethernet LAN port	1 / 0 (FE) ^[1]	[1] WAN port(s) can be configured as LAN port(s) via the Web Admin.
Router Throughput	100Mbps ^[2]	[2] Router Throughput and PepVPN/SpeedFusion Throughput is based on Ethernet frame sizes of 1280 or 1518 bytes. Actual performance can vary across different networking environments. Figures apply to the latest hardware revision. The throughput result is tested with DHCP/Static IP.
SpeedFusion VPN Throughput (No Encryption)	40Mbps ^[2]	[2] Router Throughput and PepVPN/SpeedFusion Throughput is based on Ethernet frame sizes of 1280 or 1518 bytes. Actual performance can vary across different networking environments. Figures apply to the latest hardware revision. The throughput result is tested with DHCP/Static IP.
SpeedFusion VPN Throughput (256-bit AES)	20Mbps ^[2]	[2] Router Throughput and PepVPN/SpeedFusion Throughput is based on Ethernet frame sizes of 1280 or 1518 bytes. Actual performance can vary across different networking environments. Figures apply to the latest hardware revision. The throughput result is tested with DHCP/Static IP.
Number of Cellular Modem	1 or 2	

Interfaces

Maximum Ethernet WAN / LAN port configuration	1 WAN with 0 LAN, 0 WAN with 1 LAN
SFP LAN / WAN	No
Serial Interface	No
Wi-Fi AP	No
Wi-Fi WAN	No
USB WAN	No

Module Expansion **No**

Performance

Number of Recommended Users **1-60**

Maximum Number of Controlled AP / Switch **No**

Wireless details

Cellular Modem Category options **2x CAT-3,
1x CAT-4,
2x CAT-4,
2x CAT-6**

5G support **No**

SIM Slots **2 (no redundant slots)**

SIM Card Size **Micro-SIM (3FF)**

Wi-Fi Radio **No**

Wi-Fi Antenna Transmit Power (2.4GHz, single chain) **No**

Wi-Fi Antenna Transmit Power (5GHz, single chain) **No**

Multiple SSIDs **No**

GPS **Yes**

RemoteSIM (used in SIM Injector) **Yes (HW2+)**

FusionSIM **Yes (HW2+)**

Peplink eSIM Data Plans **No**

BYO eSIM **No**

Features

SpeedFusion Hot Failover	Yes
SpeedFusion Smoothing	Yes
SpeedFusion Bandwidth Bonding	Yes
SpeedFusion Connect	Yes (HW2+)
SpeedFusion Relay Mode (Server)	Yes
Drop-In Mode	Yes
High Availability	No
Peplink AP Series Management	No
Remote AP & Multiple Config Profiles Management	No
Switch Controller	No
WAN as LAN	Yes
LAN Bypass	No
InTouch	Yes
Virtual WAN	No
Synergy Mode (Controller)	No
Synergized Device	No
Application and Web Blocking	Yes
Web Content Filtering	Lite
IP Passthrough	No
IPv6	No
x.509 Certificate	Yes
Captive Portal	Yes

GPIO	No
Ignition Sensing	No
Netflow Support	Yes
LACP (802.3ad) NIC Bonding	No
Jumbo Frame Support	No
Internal Storage for Edge Computing	No
External Storage via USB Port	No
Dead Reckoning	No

Core Functionality

Inter-VLAN Routing	Yes
802.1q VLANs Supported	16
Port-Based VLAN	Yes
Load Balancing Algorithms	8
Load Balancing & Failover	Yes
Inbound Load Balancing	No
InControl 2 Cloud Management	Yes
InControl GPS Fleet Management	Yes

Advanced QoS Functionality

Bandwidth Usage Monitoring	Yes
QoS for VoIP and E-Commerce	Yes
User Groups Bandwidth Control	Yes

VPN Functionality

SpeedFusion VPN	Yes
Number of SpeedFusion VPN Peers	2
IPsec VPN	Yes
Number of IPsec Tunnels	5
L2TP VPN / Open VPN / PPTP VPN Server	Yes
Maximum PPTP / L2TP / OpenVPN Users	3
Remote RADIUS / LDAP authentication in Remote User Access	No
Number of OpenVPN Tunnel (Site to Site)	5
Number of GRE Tunnel (Site to Site)	5

Hardware

Enclosure	Indoor, Metal
4pin Molex Micro-Fit Connector	No
Terminal Block Power Connector for Mobile / Vehicular Deployment	Yes
AC Adapter or PSU	No
Input voltage	DC 12–24V,
PoE Input	No
PoE Output	No
USB Power Input	No

Nominal Power Consumption	NA
Maximum Power Consumption	15W
Dimensions in inches	2.95 x 3.25 x 1.65 inches
Dimensions in mm	75 x 83 x 42 mm
Weight (Pound)	0.77 pound
Weight (Gram / Kilogram)	350 grams
Operating Temperature	-40°–149°F, -40°–65°C
Humidity	15%–95% (non-condensing)
Rack-mount	No
Dual Hot Swap Power Supply	No

Warranty Info

Warranty	1-Year Limited Warranty
----------	--------------------------------